



LineGard | PGFS Series

30 Amp Multi-Phase Permanent Series (Splice-In) GFCI

INTRODUCTION

The LineGard™ 30 Amp Permanent Series is an industrial grade ground fault interrupter device designed and manufactured by North Shore Safety, Ltd., a leader in innovated safety products. The unique design offers the flexibility of splicing in protection of a GFCI anywhere within the length of the circuit run, making it ideal for both new and existing applications. Unlike breaker style GFCI's which have limitations of circuit length from the service panel, the PGFS series can be integrated directly into a circuit or paired in tandem with an approved receptacle and enclosure.

Available with an operating voltage of 120/240 VAC dual voltage, 3Ø 120/208 VAC, 3Ø 240 VAC (certified to CSA 22.2 only), 3Ø 208 VAC or 3Ø 277 VAC (UL 1053 compliant), all units have 18" splicing leads and a 3/4" NPT fitting to allow connection to 3/4" PVC, EMT, burial and flexible conduits. All units are MADE IN THE USA and are listed per UL 943 and CSA 22.2 No.144

FEATURES

- Power and fault status indicators
- Double insulated user interface
- Industrial design for rough service
- Chemical and UV resistant enclosure
- cULus Listed as a Class A GFCI per UL 943 and CSA 22.2 No. 144
- 30 amp configurations in 120/240 VAC 4-wire, 3Ø 120/208 VAC 5-wire, 3Ø 240 VAC 4-wire, 3Ø 208 VAC 4-wire, 3Ø 277 VAC 4-wire (UL 1053)
- NEMA 4X and 6P wet location rated (indoor / outdoor)
- Available in automatic or manual reset configurations¹

SPECIFICATIONS

Listing Type	cULus Listed Class A UL 943 CSA 22.2 No. 144
Rated Supply Voltage	120/240 VAC Dual Voltage, 120/208 VAC 3Ø, 240 VAC 3Ø (CSA only), 208 VAC 3Ø, 277 VAC 3Ø (UL 1053)
Rated Current	Up to 30 Amps or rating of wiring device and/or cable
Horse Power	1HP@120 VAC, 3HP@240 VAC
Trip Level	5mA +/-1mA
Operating Frequency	60 Hz
Reset Type¹	Automatic or Manual
Phase	Dual voltage and 3 phase
Response Time	25mS max
Operating Temperature	-35°C to 66°C
Operating Voltage Range	85% to 110% of rated VAC
Let-Go Voltage	60% of supply voltage
Open Neutral Protection	Trips upon loss of neutral
Grounded Neutral Protection	Trips if ground and neutral touch at load side

1. Manual configuration should be specified if automatic start-up after power restoration of circuit power creates an unsafe condition.

2. Applicable models only

This document is generated from the AIRPAX™ full-line catalog #2455005000 printed in USA, January 2011

BUSINESS CENTERS

Sensata Technologies

807 Woods Road
Cambridge, MD 21613, USA
Phone: +1 410-228-1500
Brands: Airpax™

Sensata Technologies Inc.

529 Pleasant Street
Attleboro, MA 02703, USA
Phone: +1 508-236-3287
Brands: Klixon™, Sensata Technologies™

Sensata Technologies

4467 White Bear Lake Parkway
St. Paul, MN 55110, USA
Phone: +1 800-553-6418
Brands: Dimensions™

Sensata Technologies Holland B.V.

Kolthofsingel 8
7602 EM Almelo, The Netherlands
Phone: +31 546 87 95 55
Brands: Klixon™, Sensata Technologies™

Sensata Technologies China Co., Ltd.

Novel Plaza, 8th Floor
128 Nanjing Road West
Shanghai, 20003
People's Republic of China
Phone: +86 21 23061500
Brands: Klixon™, Sensata Technologies™

Sensata Technologies Korea Ltd.

29F, Trade Tower
159-1 SamSung-Dong, KangNam-Ku, Seoul
135-729, Korea
Phone: +81-2-551-2918
Brands: Klixon™, Sensata Technologies™

Sensata Technologies Japan Ltd.

305, Tanagashira
Oyama-cho, Sunto-gun, Shizuoka-ken
Japan, 410-1396
Phone: +81 550 78 1211
Brands: Klixon™, Sensata Technologies™

Sensata Technologies Nihon-Airpax

6-3, Chi Yoda 5 Chome
Saitama-Ken
Japan, 350-0214
Phone: +81 492 83 7575
Brands: Airpax™



Important Notice: Sensata Technologies (Sensata) reserves the right to make changes to or discontinue any product or service identified in this publication without notice. Sensata advises its customers to obtain the latest version of the relevant information to verify, before placing any orders, that the information being relied upon is current. Sensata assumes no responsibility for infringement of patents or rights of others based on Sensata applications assistance or product specifications since Sensata does not possess full access concerning the use or application of customers' products. Sensata also assumes no responsibility for customers' product designs.

<http://airpax.sensata.com/>